











ZHENGZHOU KBT INSTRUMENT TRANSFORMER CO., LTD.


		Technical Data					
		Rated Primary Current(A)	Accuracy Class Combination	Rated Output(VA)	Rated Short-time Thermal Current(KA/s)	Rated Dynamic Current(KA)	
1	LZZJ-10Q Current Transformer		20	0.2S	10 15 20	100In	250In
			30,40			100In	250In
			50,75			100In	250In
			100-150			100In	250In
			200			100In	250In
			300-400			100In	250In
			500-600			100In	250In
			800-1000			100In	250In
2	LZZBJ9-10A Current Transformer		Technical Data				
			Rated Primary Current(A)	Accuracy Class Combination	Rated Output(VA)	Rated Short-time Thermal Current(KA/s)	Rated Dynamic Current(KA)
			20-75	0.5/10P10 0.2/10P10 0.2S/10P10 0.2/0.5/10P10 0.2S/0.5/10P10	15/20 15/20 10/20 15/15/15 10/15/15	100In	250In
			100			21	52.5
			150-200			31.5	80
			300-400			45	112.5
			500-800			63	130
1000-1200	80	160					
3	LZZBJ9-10B Current Transformer		Technical Data				
			Rated Primary Current(A)	Accuracy Class Combination	Rated Output(VA)	Rated Short-time Thermal Current(KA/s)	Rated Dynamic Current(KA)
			20-300	0.5/10P10 0.2/10P10 0.2S/10P10	15/15 10/15	100In	250In
			400			45	112.5
500-600	63	130					
	4	LZZBJ9-10C Current Transformer				Technical Data	
Rated Primary Current(A)				Accuracy Class Combination	Rated Output(VA)	Rated Short-time Thermal Current(KA/s)	Rated Dynamic Current(KA)
20-200				0.2S/0.5/5P10 0.2S/5P10/5P10 0.2S/0.2S/10P10/10P10 0 0.2S/0.5/10P10/10P10	10/15/30 10/20/20 10/15/15/15 10/15/15	120In	306In
300						100In	255In
400						75In	192In
500						60In	153In
600-800						50In	127.5In
1000							

5	LJZN1-10 Current Transformer		Technical Data				
			Rated Primary Current(A)	Accuracy Class Combination	Rated Output(VA)	Rated Short-time Thermal Current(KA/s)	Rated Dynamic Current(KA)
			20	0.2S	10 15	5/2	12.5
			30,40			8/2	20
			50,60			10/2	25
			75			16/2	40
			100,150,200			20/2	50
			300,400,500			25/4	63
			600,,750			31.5/4	80
100,012,502,000	40/4	100					
6	LFZZJ-12 Current Transformer		Technical Data				
			Rated Primary Current(A)	Accuracy Class Combination	Rated Output(VA)	Rated Short-time Thermal Current(KA/s)	Rated Dynamic Current(KA)
			5-15	0.2S	10	150In	375In
			20-25			5	12.5
			30-40			8	20
			50-60			10	25
			75			16	40
			100-200			20	50
			300-500			25	63
600-800	31.5	80					
7	LZZW-10 Current Transformer		Technical Data				
			Rated Primary Current(A)	Accuracy Class Combination	Rated Output(VA)	Rated Short-time Thermal Current(KA/s)	Rated Dynamic Current(KA)
			50-300	0.2/10P 0.2S/10P 0.2/0.5/10P 0.2S/0.5/10P	15/30 15/30 15/20/30 15/20/30	100In	255In
			400			45	112
			500			63	130
600							
8	LZZB1-35W Current Transformer		Technical Data				
			Rated Primary Current(A)	Accuracy Class Combination	Rated Output(VA)	Rated Short-time Thermal Current(KA/s)	Rated Dynamic Current(KA)
			20-75	0.5/10P10 0.2/10P10 0.2S/10P10 0.2/0.5/10P10 0.2S/0.5/10P10 0.2S/0.5/10P10/10P10	20/50 20/50 15/20/30 15/20/30 15/20/30/30	100In	255In
			100			21	52.5
			150-200			31.5	78.7
			300-400			63	157.5
			500-600			80	200
			800-1000				
			1200-1500				
1800-2000	140	200					







1	JDZX10-10A Voltage Transformers		<b>Technical Data</b>			
			Rated Voltage Ratio(kV)	Accuracy Class Combination	Rated Output(VA)	
			10/√3/0.1/√3/0.1/√3	0.2/3P 0.5/3P	15/40 20/40	
2	JDZX9-35 Voltage transformers		<b>Technical Data</b>			
			Rated Voltage Ratio(kV)	Accuracy Class Combination	Rated Output(VA)	Thermal limiting output(VA)
			35/√3/0.1/√3/0.1/3	0.2/6P(3P) 0.5/6P(3P)	40/100 80/100	600
3	JDZXF9-35 Voltage transformers		<b>Technical Data</b>			
			Rated Voltage Ratio(kV)	Accuracy Class Combination	Rated Output(VA)	Thermal limiting output(VA)
			35/√3/0.1/√3/0.1/√3/0.1/3	0.2/0.2/6P(3P) 0.2/0.5/6P(3P) 0.5/0.5/6P(3P)	10/10/100 10/30/100 30/30/100	300
4	JDZQ(X)N-10 Voltage transformers		<b>Technical Data</b>			
			Rated Voltage Ratio(kV)	Accuracy Class Combination	Rated Output(VA)	
			10/0.1 10/√3/0.1/√3	0.2 0.5	5 10 15 20	

5	JDZ10-10C3 Voltage transformers		<b>Technical Data</b>			
			Rated Voltage Ratio(kV)	Accuracy Class Combination	Rated Output(VA)	Thermal limiting output(VA)
			10/0.1	0.2 0.5	15	300
6	JDZ10-6A JDZ10-10A JDZF10-6A JDZF10-10A JDZX10-10AG		<b>Technical Data</b>			
			Rated Voltage Ratio(kV)	Accuracy Class Combination	Rated Output(VA)	Thermal limiting output(VA)
			6/0.1	0.5	30	150
			10/0.1	0.2	15	
			6/0.1/0.1	0.2/0.2 0.2/0.5	10/10 10/15	
			10/0.1/0.1	0.5/0.5	15/15	
10/√3/0.1/√3/0.1/3	0.2/3P 0.5/3P	15/40 20/40				
7	JDZ-10Q JDZF-10Q JDZ-6Q JDZF-6Q		<b>Technical Data</b>			
			Rated Voltage Ratio(kV)		Accuracy Class Combination	
			10/0.1		0.2 0.2 0.5	
			10/0.1/0.1 10/0.1/0.22		0.2/0.5 0.2/3.0	
			6/0.1		0.2 0.2 0.5	
			6/0.1/0.1 6/0.1/0.22		0.2/0.5 0.2/3.0	
8	JDZF-10W2 Voltage transformers		<b>Technical Data</b>			
			Rated Voltage Ratio(kV)	Accuracy Class Combination	Rated Output(VA)	
			10/0.1/0.22	0.5/3.0	30/300	
9	JDZ-10W(R) Voltage transformers		<b>Technical Data</b>			
			Rated Voltage Ratio(kV)	Accuracy Class Combination	Rated Output(VA)	



10		<b>Technical Data</b>			
		Rated Voltage Ratio(kV)	Accuracy Class Combination	Rated Output(VA)	Thermal limiting output(VA)
		35/ $\sqrt{3}$ /0.1/ $\sqrt{3}$ /0.1/3	0.2/6P 0.5/6P	40/100 100/100	600
JDZXF-35W	35/ $\sqrt{3}$ /0.1/ $\sqrt{3}$ /0.1/3/0.1/ $\sqrt{3}$	0.2/0.2/6P 0.2/0.5/6P	20/20/100 20/30/100	600	



		BH-0.66 Low-voltage transformer Technical data					
	Current Ratio(A)	Rated Output(VA)					No. of Through Core Turns
		Level 1	Grade 0.5	Grade 0.5S	Grade 0.2	Grade 0.2S	
BH-0.66 30III 	150/5	5	5	5	5		1
	200/5	10	5	5	5	5	1
	250/5	10	5	5	5	5	1
	300/5	10	5	5	5	5	1
	400/5	10	5	5	5	5	1
	500/5	10	10	10	10	5	1
	150/1	5	5				1
	200/1	5	5				1
	250/1	5	5				1
	300/1	5	5				1
	400/1	5	5				1
	300/5	10	10				1
	400/5	10	10				1
	BH-0.66 50III 	500/5	10	10	10	10	5
600/5		10	10	10	10	5	1
750/5		10	10	10	10	5	1
800/5		10	10	10	10	5	1
1000/5		10	10	10	10	5	1
1200/5		20	20	20	20	5	1
300/1		10	10				1
400/1		10	10				1
500/1		10	10				1
600/1		10	10				1
750/1		10	10				1
800/1		10	10				1
1000/1		10	10				1
BH-0.66 80III 		500/5	10	10	10		
	600/5	10	10	10			1
	750/5	10	10	10	5		1
	800/5	10	10	10	5		1
	1000/5	10	10	10	5		1
	1200/5	20	20	20	5		1
	1500/5	20	20	20	10		1
	2000/5	30	30	30	10		1
	2500/5	30	30	30	10		1
	500/1	10					1
	600/1	10					1
	750/1	10					1
	800/1	10					1
	1000/1	10					1
BH-0.66 120III 	1200/1	20	20				1
	1500/1	20	20				1
	2000/1	30	30				1
	2500/1	30	30				1
	3000/1	30	30				1
	1000/5	10	10	10	10		1
	1200/5	20	20	20	20	5	1
	1500/5	20	20	20	20	10	1
	2000/5	30	30	30	30	10	1
	2500/5	30	30	30	30	10	1
	3000/5	30	30	30	30	10	1



ZHENGZHOU KBT INSTRUMENT TRANSFORMER CO., LTD.

LMZ1-0.66C Low-voltage transformer		<b>Technical Parameters</b>			
		Rated Primary Current(A)	Accuracy Classes	Rated Output(VA)	Maximum Coper Bar With
		150-600	0.2S 0.5S	5	40mm
		300	0.5S	5	80mm
		400-600	0.2S 0.5S	5	
		750-1200	0.2S 0.5S	10	120mm
		600-1500	0.2S	10	
		1600-3000	0.5S	15	
LMZ1D-KBT1 LMZ2D-KBT1 LMZ3D-KBT1 LMZ4D-KBT1 LFZ1D-KBT1		<b>Technical Parameters</b>			
		Rated Primary Current(A)	Accuracy Classes	Rated Output(VA)	
		75-150	0.2S 0.5S	5、10	
		200-500		5、10	
		600-800		5、10	
		1000-1500		5、10	
		10-60		5、10	

